

## RCL04 Low-voltage mini receiver

The RCL04 mini receiver is used above all to upgrade existing systems.

Its two potential-free relay contacts make it possible to upgrade a wide variety of systems with a radio interface. Converting a garage door motor is just as easy as integrating Easywave transmitters in complex home call systems.

The RCL04 is powered by 12-24 V AC/DC and can be programmed with up to 32 transmission codes. Technically speaking, the RCL04 is identical to the RCL03 except with regard to its housing, which is protected against dust and water.



RCL04E5002-01-01K

### Technical specifications

Coding	Easywave Up to 32 transmitters can be programmed.
Frequency	868.30 MHz
Channels	2
Power supply	12-24 V AC/DC
Power consumption	0.4 W standby at 24 V DC 0.8 W standby at 24 V AC
Operating modes	DEADMAN (maximum 36 seconds) ON/OFF (2-button operation) PULSE (1 second) ROLLER BLIND MOTOR CONTROL (2-button operation) ROLLER BLIND MOTOR CONTROL (3-button operation / 4-button operation)
Outputs	2 potential-free relay contacts (changeover contacts)
Maximum contact load	
- AC	24 V / 1 A / 24 VA
- DC	30 V / 1 A / 30 W
Operating temperature	-20 °C to +60 °C
Dimensions	72 x 114 x 36 mm
Color	white similar to RAL 9003

### Scope of delivery

- Mini receiver
- Adhesive pad
- Operating manual

### Accessories (optional)

RCL03-ACC-01-00P	2x cable assembly length 45 cm
------------------	--------------------------------



RCL03-ACC-01-00P

### Models

#### Product numbers

RCL04E5002-01-01K

#### Description

Low-voltage mini receiver 2-channel, white

### Wiring diagram

